

Exit Sign

Altare

8 watt semi-decorative curved exit sign

Viewing Distance

32 Metres

Product Description

A superbly styled curved low profile exit sign incorporating an energy efficient T5 fluorescent lamp ideally suited to prestigious installations. The Altare has a viewing distance of 32 metres and also provides downward illumination for the escape route and the door threshold for improved safety.

Product Features

- Stylish curved body
- Four colour finishes available to suit the application
- White, Chrome, Silver and Polished Brass
- · A comprehensive range of screen printed legends available
- Premium sub components assure a trouble free service life
- Designed to BS EN 60598-2-22

Applications

- Commercial premises
- Hotels
- Restaurants
- · Reception areas











8 watt semi-decorative curved exit sign

Technical Specifications

- High temperature NI-CD rechargeable batteries
- Constant current changer
- Re-Charge period 24 hours
- Ambient temperature 0-25 degrees centigrade
- Three hour duration in the event of a mains failure

Dimensions

Length 440mm x height 220mm x depth 65mm

Finishes

Add suffix to product code













White RAL9010

Black RAL9005

Silver RAL9006

Polished Chrome

Polished Brass

Satin Nickel

Control Options

- AD Intelligent addressable ballast
- ST Self test

Order Codes

 ${\it Please Note:} The appropriate exit sign and legend should be ordered separately.$

Order Code	Weight	Light Source	Mode	Duration
EZ/ALT/18/NM3/*	1 x 8	T5 Linear Fluorescent	Non-Maintained	High Frequency
EZ/ALT/18/NM3/*	1 x 8	T5 Linear Fluorescent	Maintained	High Frequency

^{*} Add suffix for finish and control gear option.

EG: EZ/ALT/18/NM3/S/ST 8 watt T5 Altare non-maintained exit sign finished in silver with a self test function.

Legend Order Codes	1 1 1 → ■	₹ →■	∡ †↓■	∡ †	∡ ■
Description	AR - Arrow Right	AL - Arrow Left	AD - Arrow Down	AU - Arrow Up	NA - No Arrow
Part number	EZ/ALT/AR	EZ/ALT/AL	EZ/ALT/AD	EZ/ALT/AU	EZ/ALT/NA

EG: EZ/ALT/AR - Arrow right screen printed legend for a Altare exit sign.

